

LIGHTHOUSE[®]

USER MANUAL L/H SLFEST110 FESTOON LIGHTS

BEFORE USING FOR THE FIRST TIME

These instructions contain information necessary for safe and effective operation of this product. This product has unique features and, even if you are familiar with similar products, it is necessary to read these instructions carefully to ensure you fully understand the product. Ensure all users of the product read and fully understand these instructions. Keep these instructions with the product for future reference.

SAFETY PRECAUTIONS

WARNING: THIS LIGHTING CHAIN MUST NOT BE USED WITHOUT ALL GASKETS BEING IN PLACE

- ▶ Do not use if any of the components are damaged. If there is any doubt about the condition, do not use.
- ▶ Never attempt to modify or repair this product. Repairs carried out by unskilled people can lead to damage to the product. Please contact the manufacturer, relevant service agent or a similar qualified person to avoid this hazard.
- ▶ Only use when fully unwound.
- ▶ Do not cover when in use.
- ▶ Do not connect more than eight festoon light sets together.
- ▶ Only use the manufacturers replacement bulbs.
- ▶ All bulb holders must have a bulb fitted to maintain protection against water ingress and to prevent access to live parts.

WARNING: PROTECT THE POWER CORD FROM CONTACT WITH SHARP OBJECTS, CHEMICALS, HEAT SOURCES OR MOVING PARTS.

- ▶ The cable should be positioned such that it does not present a trip hazard or cause an obstruction to personnel or machinery.
- ▶ Do not connect to the power source until the festoon is fully fitted in its intended position.
- ▶ The first bulb holder should be positioned to provide adequate cable length to the supply point and should be suitably secured by strapping or similar restraint.
- ▶ Where practical, each bulb holder should be held in position using the fixing holes provided. When not practical, it is recommended that a cable tie or similar equivalent is used on each side of the light module.

INTENDED USE

Flexible lighting solution for illuminating worksite areas. Suitable for both indoor and outdoor operation.

These lights must **ONLY** be used for their intended purpose. Any use other than those mentioned in these instructions will be considered a case of misuse. The user, and not the manufacturer shall be liable for any damage or injury resulting from such cases of misuse. The manufacturer shall not be liable for any modifications made to the product, nor for any damage resulting from such modifications.

OPERATION

WARNING: ALWAYS ENSURE THE PLUG MATCHES THE OUTLET SOCKET AND CHECK THAT THE VOLTAGE SUPPLY IS THE SAME AS THAT SPECIFIED ON THE RATING LABEL.

- ▶ Ensure no personnel are in contact with the festoon and switch on.
- ▶ Immediately check each bulb holder is functioning correctly and that no danger is present.
- ▶ Disconnect the festoon from the power supply before removing or moving the festoon.
- ▶ Do not remove the plug from the mains supply by pulling on the power cord.

TECHNICAL DATA

PART NUMBER	L/H SLFEST110
DESCRIPTION	22M Festoon Lights
VOLTAGE	110V ~ 50Hz
BULB	10x 10W ES27 LED
CAGE MATERIAL	Plastic
PLUG TYPE	16 Amp 110V EN 60309 Industrial
POWER CORD	22M Yellow Arctic Cable
BULB SPACING	2M
IP RATING	IP44
OPERATING TEMPERATURE	-25°C to +45°C


CONTENTS



x10



x10



22m

ROUTINE INSPECTION

- ▶ Check daily to inspect for any physical damage or abrasions to the cable.
- ▶ Ensure there is no visible damage to the bulbs, bulb holders or the plug.
- ▶ If the supply cord or plug show signs of damage or wear, they must be replaced by the manufacturer, relevant service agent or similarly qualified persons in order to avoid any danger.

CLEANING

Clean each bulb with a soft dry or damp cloth when not in use. Always check the product is completely free of moisture before using again.

STORAGE

Store these lights carefully in a dry place, out of reach of children and pets.

DISPOSAL OF THIS PRODUCT

Always adhere to national regulations when disposing of electrical goods that are not longer functional and are not viable for repair. Do not dispose of this product in general household waste, instead, contact your local waste disposal authority for information on how to correctly dispose of any electrical or electronic equipment (WEEE).

GUARANTEE

Lighthouse guarantees this product to the original purchaser for a period of **ONE YEAR** against any defects in material or workmanship but shall not cover damage caused by misuse, abuse, alteration or accident. This product is intended for domestic and trade use. In the case of products used for hire, the guarantee period is restricted to **THREE MONTHS**.

It is the responsibility of the purchaser to return any faulty or damaged products to the original place of purchase within a period of **ONE YEAR**. Lighthouse cannot replace or accept returns on products that exceed this guarantee period.

LIGHTHOUSE TORCHES
Long Reach, Galleon Boulevard,
Crossways Business Park,
Dartford, Kent, DA2 6QE,
United Kingdom.

QFF DISTRIBUTION
24 Magna Drive, Magna Business Park,
Citywest Road,
Dublin 24, D24 FNYO, Ireland.



▶ www.lighthouse-torches.com



RoHS
2011/65/EU

